

JANE R - è un trasmettitore compatibile solo con il ricevitore modello **RXJR-2C**.

CANALE 1

- premere e rilasciare il tasto del ricevitore, attendere che il **LED verde** si accenda, **canale 1**
- avvicinare il telecomando **JANE R** al ricevitore e premere uno dei tasti da associare con il canale 1: l'apprendimento viene segnalato dal ricevitore con lo spegnimento di 0,5 secondi del **LED verde**
- prima dello spegnimento definitivo del led verde (durata 5 secondi) è possibile associare un secondo tasto del telecomando **JANE R**, o un altro telecomando **JANE R** con il canale 1 del ricevitore

CANALE 2

- premere e rilasciare il tasto del ricevitore: si accende il led verde, **canale 1**
- premere e rilasciare una seconda volta: si accende il **LED rosso**, canale 1
- avvicinare il telecomando **JANE R** nel ricevitore e premere uno dei tasti da associare con il **canale 2**
- l'apprendimento viene segnalato dal ricevitore con lo spegnimento di 0,5 secondi del led rosso
- prima dello spegnimento definitivo del **LED rosso** (durata 5 secondi) è possibile associare un secondo tasto del telecomando **JANE R**, o un altro telecomando **JANE R** con il canale 2 del ricevitore

Cancellazione singola

- È possibile cancellare dalla memoria del ricevitore uno o più tasti appresi dal telecomando **JANE R**
- premere 3 volte e rilasciare il tasto del ricevitore
- si accende il **LED** arancione intermittente
- avvicinare il telecomando **JANE R** al ricevitore e premere uno dei tasti che si desidera cancellare dalla memoria del ricevitore
- la cancellazione viene segnalata dal ricevitore con lo spegnimento di 0,5 secondi del led arancione
- prima dello spegnimento definitivo del **LED** arancione (durata 5 secondi) è possibile cancellare un secondo tasto del telecomando **JANE R**

Cancellazione totale

- È possibile cancellare tutti i telecomandi **JANE R** dalla memoria del ricevitore
- premere 3 volte senza rilasciare il tasto del ricevitore
- si accende il **LED** arancione intermittente
- attendere che il **LED** arancione da intermittente diventi fisso
- lasciare il tasto
- la cancellazione comprende anche le eventuali modalità programmate come la **BISTABILE** e la **TEMPORIZZATA**
- il ricevitore torna in modalità **MONOSTABILE**

JANE R - is a transmitter compatible only with the receiver model **RXJR-2C**.

CHANNEL 1

- press and release the receiver button. The green **LED** lights up, **channel 1**
- put the remote control **JANE R** close to the receiver and press the button to be associated with channel 1: the green **LED** on the receiver goes off for 0.5 seconds to confirm learning
- before the **LED** goes out completely (after 5 seconds) it is possible to associate a second remote control **JANE R** button, or a different remote control **JANE R** with channel 1 of the receiver

CHANNEL 2

- press and release the receiver button. The green **LED** lights up, **channel 1**
- press and release a second time: the red **LED** lights up, **channel 2**
- Put the remote control **JANE R** close to the receiver and press the button to be associated with **channel 2**
- the green **LED** on the receiver goes off for 0.5 seconds to confirm learning
- Before the **LED** goes out completely (after 5 seconds) it is possible to associate a second remote control **JANE R** button, or a different remote control **JANE R** with channel 2 of the receiver

Single deletion

- It is possible to delete one or more buttons learned from the remote control **JANE R** from the receiver memory
- press and release the receiver button three times
- the amber flashing **LED** lights up
- put the remote control **JANE R** close to the receiver and press the button to be deleted from the receiver memory
- deletion is confirmed by the receiver when the amber light goes out for 0.5 seconds
- before the amber **LED** goes out completely (after 5 seconds) it is possible to delete a second remote control **JANE R** button


Total deletion

- It is possible to delete all remote control **JANE R** buttons from the receiver memory
- press and the receiver button three times and hold
- the amber flashing **LED** lights up
- wait until the amber flashing **LED** becomes fixed
- release the button
- the deletion also includes any programmed modes such as **DUAL FIXED MODE** and **TIMED MODE**
- the receiver returns to **SINGLE FIXED MODE**

Caratteristiche Tecniche	
Frequenza	433.92 MHz
Banda operativa di frequenza	433.05 - 434.79 MHz - dispositivo classe 1
Potenza	1mW e.r.p.
Alimentazione	batteria litio 3v tipo (CR2032)
Codifica	codice FISSO
Numero canali	2-4



Technical Information	
Frequency	433.92 MHz
Frequency band	433.05 - 434.79 MHz - class 1 device
Power	1 mW e.r.p.
Supply	lithium battery 3v (CR2032)
Encryption	FIXED code
Number of channels	2-4



Garanzia: 24 mesi

Dichiarazione di conformità

Il fabbricante, Luigino Pellattiero, dichiara che il tipo di apparecchiatura radio JRxxx-2/JRxxx-4 è conforme alla direttiva 2014/53/UE.

Il testo completo della dichiarazione di conformità UE è disponibile al seguente indirizzo Internet: <http://italfile.it/conformita-jane-r/>

Luigino Pellattiero - Vicenza, 31.05.2017

Fabbricazione e tecnologia: 100% made in Italy

Luigino Pellattiero

Warranty: 24 months

Declaration of conformity

Hereby, Luigino Pellattiero declares that the radio equipment type JRxxx-2/JRxxx-4 is in compliance with Directive 2014/53/EU.

The full text of the EU declaration of conformity is available at the following internet address: <http://italfile.it/conformita-jane-r/>

Luigino Pellattiero - Vicenza, 31.05.2017

Manufacturing and technology: 100% made in Italy

Luigino Pellattiero